

Modbus Parameters		Default
Mode:	RTU (LSB first, apply address offset of +1 for Function 3 Holding Registers)	
Baudrate:	300 / 600 / 1200 / 2400 / 4800 / 9600 / 19200 bps	9600
Data Bit:	8	
Stop Bits:	1 or 2	1
Parity:	None / Odd / Even	None
Functions:	3 / 4	
Scan Rate:	≤ 100mS	

Register List									
Starting Address (Decimal)	Starting Register (Hex)	Parameter	Unit	Function	Read / Write	Length	Data structure	Range / Value	Default
30000	0x00	Voltage V1-N	V	3	R	2	Float	-	-
30002	0x02	Voltage V2-N	V	3	R	2	Float	-	-
30004	0x04	Voltage V3-N	V	3	R	2	Float	-	-
30006	0x06	Average Voltage L-N	V	3	R	2	Float	-	-
30008	0x08	Voltage V1-2	V	3	R	2	Float	-	-
30010	0x0A	Voltage V2-3	V	3	R	2	Float	-	-
30012	0x0C	Voltage V3-1	V	3	R	2	Float	-	-
30014	0x0E	Average Voltage L-L	V	3	R	2	Float	-	-
30016	0x10	Current I1	A	3	R	2	Float	-	-
30018	0x12	Current I2	A	3	R	2	Float	-	-
30020	0x14	Current I3	A	3	R	2	Float	-	-
30022	0x16	Average Current	A	3	R	2	Float	-	-
30024	0x18	kW1	kW	3	R	2	Float	-	-
30026	0x1A	kW2	kW	3	R	2	Float	-	-
30028	0x1C	kW3	kW	3	R	2	Float	-	-
30030	0x1E	kVA1	kVA	3	R	2	Float	-	-
30032	0x20	kVA2	kVA	3	R	2	Float	-	-
30034	0x22	kVA3	kVA	3	R	2	Float	-	-
30036	0x24	kVAr1	kVAr	3	R	2	Float	-	-
30038	0x26	kVAr2	kVAr	3	R	2	Float	-	-
30040	0x28	kVAr3	kVAr	3	R	2	Float	-	-
30042	0x2A	Total kW	kW	3	R	2	Float	-	-
30044	0x2C	Total kVA	kVA	3	R	2	Float	-	-
30046	0x2E	Total kVAr	kVAr	3	R	2	Float	-	-
30048	0x30	PF1		3	R	2	Float	-	-
30050	0x32	PF2		3	R	2	Float	-	-
30052	0x34	PF3		3	R	2	Float	-	-
30054	0x36	Average PF		3	R	2	Float	-	-
30056	0x38	Frequency	Hz	3	R	2	Float	-	-
30058	0x3A	Total net kWh	kWh	3	R	2	Float	-	-
30060	0x3C	Total net kVAh	kVAh	3	R	2	Float	-	-
30062	0x3E	Total net kVArh	kVArh	3	R	2	Float	-	-
30064	0x40	kW Max Active Power	kW	3	R	2	Float	-	-
30066	0x42	kW Min Active Power	kW	3	R	2	Float	-	-
30068	0x44	kVAr Max Reactive Power	kVAr	3	R	2	Float	-	-
30070	0x46	kVAr Min Reactive Power	kVAr	3	R	2	Float	-	-
30072	0x48	kVA Max Apparent Power	kVA	3	R	2	Float	-	-
30074	0x4A	Max I1 Current Demand	A	3	R	2	Float	-	-
30076	0x4B	Max I2 Current Demand	A	3	R	2	Float	-	-
30078	0x4E	Max I3 Current Demand	A	3	R	2	Float	-	-
30080	0x50	Max Average Current Demand	A	3	R	2	Float	-	-
30082	0x52	Run hour	hrs	3	R	2	Float	-	-
30084	0x54	kWh1 (Imp)	kWh	3	R	2	Float	-	-
30086	0x56	kWh2 (Imp)	kWh	3	R	2	Float	-	-
30088	0x58	kWh3 (Imp)	kWh	3	R	2	Float	-	-
30090	0x5A	kW1 (Exp)	kWh	3	R	2	Float	-	-
30092	0x5C	kW2 (Exp)	kWh	3	R	2	Float	-	-
30094	0x5E	kW3 (Exp)	kWh	3	R	2	Float	-	-
30096	0x60	Total kWh (Imp)	kWh	3	R	2	Float	-	-
30098	0x62	Total kWh (Exp)	kWh	3	R	2	Float	-	-
30100	0x64	kVArh1 (Imp)	kVArh	3	R	2	Float	-	-
30102	0x66	kVArh2 (Imp)	kVArh	3	R	2	Float	-	-
30104	0x68	kVArh3 (Imp)	kVArh	3	R	2	Float	-	-
30106	0x6A	kVArh1 (Exp)	kVArh	3	R	2	Float	-	-
30108	0x6C	kVArh2 (Exp)	kVArh	3	R	2	Float	-	-
30110	0x6E	kVArh3 (Exp)	kVArh	3	R	2	Float	-	-
30112	0x70	Total kVArh (Imp)	kVArh	3	R	2	Float	-	-
30114	0x72	Total kVArh (Exp)	kVArh	3	R	2	Float	-	-
30116	0x74	kVAh1	kVAh	3	R	2	Float	-	-
30118	0x76	kVAh2	kVAh	3	R	2	Float	-	-
30120	0x78	kVAh3	kVAh	3	R	2	Float	-	-
30122	0x7A	Neutral Current	A	3	R	2	Float	-	-
30124	0x7C	THD of 1st Phase Voltage	%	3	R	2	Float	-	-
30126	0x7E	THD of 2nd Phase Voltage	%	3	R	2	Float	-	-
30128	0x80	THD of 3rd Phase Voltage	%	3	R	2	Float	-	-
30130	0x82	THD of Voltage V1-2	%	3	R	2	Float	-	-
30132	0x84	THD of Voltage V2-3	%	3	R	2	Float	-	-

Starting Address (Decimal)	Starting Register (Hex)	Parameter	Unit	Function	Read / Write	Length	Data structure	Range / Value	Default
30134	0x86	THD of Voltage V3-1	%	3	R	2	Float	-	-
30136	0x88	THD of Current I1	%	3	R	2	Float	-	-
30138	0x8A	THD of Current I2	%	3	R	2	Float	-	-
30140	0x8C	THD of Current I3	%	3	R	2	Float	-	-
30684	0x2AC	Serial No.		3	R	2	Hex	-	-
30700	0x2BC	Phase Sequence Indicator		3	R	2	Integer	0: Clockwise 1: Anticlockwise 2: Invalid	-
30702	0x2BE	Existing kW Max Active Power	kW	3	R	2	Float	-	-
30704	0x2C0	Existing kW Min Active Power	kW	3	R	2	Float	-	-
30706	0x2C2	Existing kVAr Max Reactive Power	kVAr	3	R	2	Float	-	-
30708	0x2C4	Existing kVAr Min Reactive Power	kVAr	3	R	2	Float	-	-
30710	0x2C6	Existing kVA Max Apparent Power	kVA	3	R	2	Float	-	-
30712	0x2C8	Existing Max I1 Demand	A	3	R	2	Float	-	-
30714	0x2CA	Existing Max I2 Demand	A	3	R	2	Float	-	-
30716	0x2CC	Existing Max I3 Demand	A	3	R	2	Float	-	-
30718	0x2CE	Existing Max Avg. Current Demand	A	3	R	2	Float	-	-
40000	0x00	Password		4	R/W	1	Integer	0000 - 9998	1000
40001	0x01	Network Selection		4	R/W	1	Integer	0x0000: 3P4W 0x0002: 1P2W-P1 0x0003: 1P2W-P2 0x0004: 1P2W-P3	0x0000
40002	0x02	CT Secondary	A	4	R	1	Integer	5	5
40003	0x03	CT Primary	A	4	R/W	1	Integer	5 - 10000	160
40004	0x04	PT Secondary	V	4	R/W	1	Integer	173 - 415	350
40005	0x05	PT Primary	V	4	R/W	2	Integer	100 - 500k	350
40007	0x07	Slave ID		4	R/W	1	Integer	1 - 255	1
40008	0x08	Baud Rate	bps	4	R/W	1	Integer	0x0000: 300 0x0002: 600 0x0003: 2400 0x0004: 4800 0x0005: 9600 0x0006: 19200	0x0005
40009	0x09	Parity		4	R/W	1	Integer	0x0000: None 0x0001: Odd 0x0002: Even	0x0000
40010	0x0A	Stop Bit		4	R/W	1	Integer	0x0000: 1 0x0001: 2	0x0000
40011	0x0B	Backlight OFF	sec	4	R/W	1	Integer	0 - 7200	0
40012	0x0C	Factory Default		4	R/W	1	Integer	1: Set to factory setting range	-
40016	0x10	Auto Mode Pages		4	R/W	1	Integer	1 - 21	21
40017	0x11	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40018	0x12	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40019	0x13	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40020	0x14	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40021	0x15	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40022	0x16	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40023	0x17	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40024	0x18	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40025	0x19	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40026	0x1A	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40027	0x1B	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40028	0x1C	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40029	0x1D	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40030	0x1E	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40031	0x1F	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40032	0x20	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40033	0x21	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40034	0x22	Demand Interval Method		4	R/W	1	Integer	0x0000: Sliding 0x0001: Fixed	0x0000
40035	0x23	Demand Interval Duration		4	R/W	1	Integer	1 - 30	15
40036	0x24	Demand Interval Length	min	4	R/W	1	Integer	1 - 30	1
40043	0x2B	Reset Max Power		4	R/W	1	Integer	1: Reset all max power	-
40044	0x2C	Reset Energy Values		4	R/W	1	Integer	1: Reset all energy values	-
40045	0x2D	Reset Run Hour		4	R/W	1	Integer	1: Reset run hour	-
40054	0x36	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40055	0x37	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40057	0x39	Pulse Duration	sec	4	R/W	1	Integer	0.1 - 2.0	0.1
40058	0x3A	Pulse Weight	kWh	4	R/W	1	Integer	0.01 - 99.99	0.1
40059	0x3B	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40060	0x3C	Page Address Sequence		4	R/W	1	Integer	1-21 / 1-First Page; 21-Last Page	-
40063	0x3F	Reset Max Current		4	R/W	1	Integer	1: Reset max current	-